

WE FIXED ATTENUATOR SELECTOR GUIDE

P/N	Conn.	Page No.	Imp. (Ohms)	Max Freq (GHz)	Max Power (W)	Attenuator Extension (dBvalue)														
						1	2	3	4	5	6	7	8	9	10	12	15	20	30	40
ST702	2.92mm	226	50	26.5	0.5	X	X	X			X				X			X	X	
4	2.92mm	226	50	40	0.5			X			X				X			X	X	
ST704	7/16	229	50	7.5	5	X	X	X			X				X			X	X	X
6	7/16	229	50	7.5	10	X	X	X			X				X			X	X	X
ST703	7/16	229	50	7.5	25	X	X	X			X				X			X	X	X
9	7/16	229	50	7.5	50						X				X			X	X	X
ST704	7/16	229	50	1.5	100						X				X			X	X	X
0	7mm	226	50	18	2	X	X	X			X				X			X	X	
ST704	BNC	230	50	2	1	X	X	X			X				X			X	X	
1	BNC	230	50	4	2	X	X	X			X				X			X	X	
ST704	BNC	230	50	2	10		X	X			X				X			X	X	
2	BNC	230	50	1	100			X			X				X			X	X	X
ST704	N	227	50	2	1			X			X				X			X	X	X
3	N	227	50	12.4	2	X	X	X			X				X			X	X	X
ST702	N	227	50	18	2	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
3	N	227	50	18	5	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
ST700	N	228	50	12.4	10	X	X	X			X				X			X	X	X
0	N	227	50	2	10	X	X	X			X				X			X	X	X
ST704	N	228	50	18	10		X	X			X				X			X	X	X
9	N	228	50	18	25	X	X	X			X				X			X	X	X
ST702	N	228	50	18	50	X	X	X			X				X			X	X	X
5	N	228	50	1.5	100						X				X			X	X	X
ST702	N	228	50	1	300						X				X			X	X	X
6	N	228	50	0.5	500	X	X	X			X				X			X	X	
ST700	SMA	226	50	2	1	X	X	X			X				X			X	X	
2	SMA	226	50	3	2	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
ST704	SMA	226	50	6	2	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
7	SMA	226	50	12.4	2	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
ST700	SMA	226	50	18	2	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
4	SMA	227	50	18	5	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
ST701	SMA	227	50	18	10	X	X	X			X				X			X	X	X
4	SMA	227	50	18	25	X	X	X			X				X			X	X	X
ST704	SMA	227	50	18	50	X	X	X			X				X			X	X	X
8	SMA	227	50	1.5	100						X				X			X	X	X
ST701	TNC	228	50	2	1						X				X			X	X	X
0	TNC	228	50	12.4	2	X	X	X			X				X			X	X	X
ST701	TNC	228	50	18	2	X	X	X			X				X			X	X	X
5	TNC	229	50	18	5	X	X	X			X				X			X	X	X
ST701	TNC	229	50	18	10	X	X	X			X				X			X	X	
7	TNC	229	50	18	25	X	X	X			X				X			X	X	X
ST701	TNC	229	50	18	50	X	X	X			X				X			X	X	X
9	TNC	229	50	1.5	100	X	X	X			X				X			X	X	X
ST702	BNC	230	75	1	1						X				X			X	X	X
1	BNC	230	75	4	2						X				X			X	X	X
ST703	F	230	75	1	2	X	X	X			X				X					
1	N	230	75	1	1	X	X	X			X				X					
ST703	N	230	75	4	2	X	X	X			X				X					
2						X	X	X										X	X	
ST716						X	X	X										X	X	

Attenuation



+91 7217885948

www.rfconnector.in

pradeep@rfconnector.in

