



and the certificate of drivers will be shown on each item.























LED light provides convenient work in dark

Battery power indication

- 1300mAh Li-ion Battery. Long life battery pack, anti-pollution.
- Dual angle adjustment allows straight and angle use
- 6+1 Adjustable torque settings, maximum output torque up to 3 Nm
- Quick release chuck, switch for forward or reverse rotation.
- Battery power indication
- LED light provides convenient work in dark
- Over charging and discharging protection

Model No.		PT-1361A	PT-1361F
Main body	Torque setting	6+1 positions	
	Rated no load speed		
		3 Nm (30.6 kgf-cm/26.55 lbf-in)	
	·	Hex 1/4 (6.3mm) quick release chuck	
	Special function	Switch for forward or reverse rotation, 2 different angle settings Includes LED Light. LED Battery Power Status Indicator	
	Overall length: straight	235mm (L)	
	Overall length: angled	170(L)x145(H)mm	
Battery	Battery type	Li-ion	
	Battery voltage	3.6V	
	Battery capacity	1300mAh	
	Charging time	3-5 hours	
	Free running time	60 min	
Adapter	Model No.	5PT-1361-ADA	5PT-1361-ADF
	Input voltage	120V AC 60Hz	230V AC 50Hz
	Output voltage	DC 6V 300mA	
	Adapter plug	A	F •••
Standard Accessories	Model No.	5PT-1361-P1 (4 pcs/set)	
	Bits set	4pcs 50mm driver bits: ⊕ 5.0, 6.0 ⊕ #1, #2,	
Individual packing		Double blister	