



## TO-MTF –TYPE CIRCULAR PRE INSTALING TERMINAL

Subordinate categories: head and connector terminal

**Lead section :0.5-1 .5 mm<sup>2</sup> (AWG 22-16) Max Current: I<sub>max</sub> = 19A**

Model Item No	US-made screw bolt No.	Bolt Diameter d2 (mm)	Size Dimension (mm)					Color,
			B	L	F	E	D	
RV1.25-32	# 4	3.2	5.7	17.8	4.95			
RVS1.25-3.5	# 6	3.7	5.7	17.8	4.95			
RVM1.25-3.5	# 6	3.7	6.6	20.1	6.3			
RVL1.25-3.5	# 6	3.7	8.0	21.5	7.0			
RVS1.25-4	# 8	4.3	6.6	20.1	6.3			
RVL1.25-4	# 8	4.3	8.0	21.5	7.0	5.0	4.3	Red
RVS1.25-5	# 10	5.3	8.0	21.5	7.0			
RVL1.25-5	# 10	5.3	9.8	23.0	8.5			
RVS1.25-6	1 / 4	6.4	9.8	23.0	8.5			
RV1.25-6	1 / 4	6.4	11.6	27.5	11.1			
RV1.25-8	5 / 16	8.4	11.6	27.5	11.1			
RV1.25-10	3 / 8	10.5	13.6	31.6	13.9			
RV1.25-12	1 / 2	13.0	19.2	36.0	16.5			




**Lead section :1.5-2 .5 mm<sup>2</sup> (AWG 16-14) Max Current: I<sub>max</sub> = 27A**

Model Item No	US-made screw bolt No.	Bolt Diameter d2 (mm)	Size Dimension (mm)					Color,
			B	L	F	E	D	
RV2-3.2	# 4	3.7	6.6	17.8	4.3			
RVS2-3.5	# 6	3.7	6.6	17.8	4.3			
RVM2-3.5	# 6	3.7	6.6	21.0	7.0			
RVL2-3.5	# 6	3.7	8.5	22.5	7.75			
RVS2-4	# 8	4.3	6.6	21.0	7.0			
RVL2-4	# 8	4.3	8.5	22.5	7.75	5.0	4.9	Blue Blue
RVS2-5	# 10	5.3	8.5	22.5	7.75			
RVL2-5	# 10	5.3	9.5	22.5	7.25			
RV2-6	1 / 4	6.4	12.0	27.6	11.0			
RV2-8	5 / 16	8.4	12.0	27.6	11.0			
RV2-10	3 / 8	10.5	13.6	30.2	13.9			
RV2-12	1 / 2	13.0	19.2	36.5	16.5			



**Lead section :2.5-4mm<sup>2</sup> (AWG 14-12) Max Current: I<sub>max</sub> = 37A**

Model Item No	US-made screw bolt No.	Bolt Diameter d2 (mm)	Size Dimension (mm)				Color,
			B	L	F	E D	
RV3.5-4	# 8	4.3	8.0	24.5	7.7	13.0 6.2 Black B	
RVS3.5-5	# 10	5.3	8.0	24.5	7.7		
RVL3.5-5	# 10	5.3	12.0	27.9	7.7		
RV3.5-6	1 / 4	6.4	12.0	27.9	7.7		
RV3.5-8	5 / 16	8.5	15.0	33.5	13		
RV3.5-10	3 / 8	10.5	15.0	33.5	13		



**Conductor cross-section :4-6mm<sup>2</sup> (AWG 12-10) Max Current: I<sub>max</sub> = 48A**

Model Item No	US-made screw bolt No.	Bolt Diameter d2 (mm)	Size Dimension (mm)				Color,
			B	L	F	E D	
RV5.5-3.5	# 6	3.7	7.2	21.4	5.9	13.0 6.7 Yellow Yellow	
RVS5.5-4	# 8	4.3	7.2	21.4	5.9		
RVL5.5-4	# 8	4.3	9.5	25.5	8.3		
RV5.5-5	# 10	5.3	9.5	25.5	8.3		
RV5.5-6	1 / 4	6.4	12.0	31.5	13.0		
RV5.5-6	5 / 16	8.4	15.0	33.7	13.7		
RV5.5-10	3 / 8	10.5	15.0	33.7	13.7		
RV5.5-12	1 / 2	13.0	19.2	38.1	16.0		



**SYNERGY TELECOM (P) LTD.**

13-15, 6/5 Flats, E-Block, Vistas Park, New Delhi - 110 018 (INDIA)  
 Phone: +91-11-26533349 Fax: +91-11-26533400 Mobile: +91-9810338694  
 Email: pradeep@connectorhouse.com, MSN: pradeepgrows@synergy@hotmail.com  
 PRINCIPAL SITE: <http://www.vinncom.info> Skype Account: pradeepg  
 My trademark ID: synergytelecom [www.zkangsd.com/info](http://www.zkangsd.com/info)