

Synergy Telecom P Ltd.

Synergy Telecom (P) Ltd **ATTENUATOR 2W 10dB 6 GHz** Synergy Telecom (P) Ltd

Synergy Telecom (P) Ltd **PART NO-SYATF021006N1** Synergy Telecom (P) Ltd



Electrical Specification

Characteristic Impedance	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	50 ohm
Frequency Range	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	0~6000Mhz
Input VSWR	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	≤ 1.19
Output VSWR	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	≤ 1.29
Attenuation	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	10dB
Attenuation Accuracy	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	≤ 1.0 dB
IMD	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	-110 dBc
Input Connector	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	N male
Output Connector	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	N female
RoHS	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Synergy Telecom (P) Ltd	Compliance

Environmental

Temperature Range Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd **-33°C ~ +55°C**

13-15 RPS flats, E-block, Vikaspuri, N Delhi-110018, India
 Phone-91 11 28533349, Mobile-91 98101 38894, Fax -91 11 2853 1435,
 E-mail : pradeep@rfconnectorhouse.com, Website : http://www.rfconnector.info/

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd